



HST-2001 ACV

Digital Portable Meter



CE



Holster CCO-2001

Features

- Big-size LCD (112 x 59mm)
- Backlight function.
- Analog scale with Bar-graph for viewing. (100 bars)
- 10000 counts (high resolution).
- ACV Ranges: 99.99mV~800.0V.
- 5 manual ranges controlled by rotary switch.
- Data Hold function
- Low battery indication
- 9V power supply
- Best resolution of 0.01mV (10uV)
- Precision meter for factory maintenance, field servicing and educational purposes.
- With an optical USB to RS-232 data transmission cable (ACV-R).
- 2 optical LEDs are built-in for data transfer (ACV-R).
- Well isolated to contact (ACV-R).
- The software is included (Compact disc). (ACV-R).

Specifications

AC Voltmeter

Ranges	Resolution	Accuracy
100.00mV	10uV	
1000.0mV	100uV	
10.000V	1mV	50/60Hz : $\pm(0.3\%rdg+5dgt)$
100.00V	10mV	40~400Hz : $\pm(0.5\%rdg+6dgt)$
800.0V	100mV	

General

Operating Temperature & Humidity	0°C ~ 40°C, 80% Max. R. H.
Storage Temperature & Humidity	-10°C ~ 50°C, 80% Max. R. H.
Dimensions (with holster)	177 (L) x 200 (W) x 105 (D) mm
Weight (battery included)	Approx. 1190g
Power source	1.5V (AA) x 6
Safety standard	EN 61010-1, EN 61326-1

Accessories

- Instruction manual.
- Batteries.
- Data transmission cable CA-232 (ACV-R).
- Compact disc(CD) for PC interface (ACV-R).
- Test leads (Optional).
- Alligators (Optional).
- Holster (Optional).