



# Model LVD-25

## Low Voltage Detector



The non-contact Voltage Detector is intended to check for the presence of AC Voltage, signaling the user with a vibration alarm and a flashing LED.

It's used to detect voltage in outlets, lighting fixtures, circuit breakers, wires, and cables or to find a break in a wire

### Features

- Protection class : IP65
- Vibration alarm and bright LED when voltage is present.
- Designed for non-contact voltage detection.
- Can be used to find a break in a wire.
- Flashlight function.
- ON/OFF switch for longer battery life.

### Specifications

Voltage detection	50V~1000V AC
Frequency	50~500 Hz
Measurement category	CAT III 1000V
Indication	Vibration and LED
Temperature	0 ~ 40°C
Humidity	Less than 80% R.H.
Altitude	2000 m (6500 feet) maximum
Power source	1.5V (AAA) battery x 2
Dimension	167 (L) × 27 (W) × 29.5 (D) mm
Weight	Approx. 51g (batteries included)
Safety standard	EN 61010-1 EN 61326-1 IEC 61000-4-2 IEC 61000-4-3 IEC 61000-4-8

