weasuring the World

HPW1 DC Power Supply

Digital Panel Meters

The PW 1.0 is a regulated 0.5 amp power supply that accepts 24 VAC at the input and provides 24 VDC at the output. Field voltage adjustments may be made using only a screwdriver. The power supply is provided with a mounting track for easy field application. These low-cost power supplies feature good regulation and have full overcurrent protection.

Features

- Low cost
- · Regulated DC output
- Snap-track mounted
- · Screw terminals with pressure plates

Specifications

Voltage

Input: 24 VAC, 50/60 Hz

Output: 24 VDC (full wave rectified and regulated)

adjustable 1.5 V - 29 VDC

Output Current: 0.5 amps
Over-current Protection: 1 amp fuse

General

Operating Temperature: 0 to 55°C (32 to 130°F)
Max. Humidity: 95% RH, noncondensing

Weight: 0.25 lb.


Mounting: snap-track included

Ordering Information


Part Number


PW1.0 DC Power Supply





Dimensions





Hoyt Electrical Instrument Works, Inc.

23 Meter Street Penacook, NH 03303 Phone: (800) 258-3652

Fax: (603) 753-9592 Email: sales@hoytmeter.com www.hoytmeter.com

Page 1 (1)