# Measuring the World

# Model 279A HD

# High and Low Voltage Detector

## 279A HD High and Low Voltage Detector

#### **Features**

- Compact and light weight
- Self-test function
- Voltage detection: 80V~11.4kV AC
- Waterproof: IP65
- Identify Line (Phase) and Neutral
- Operation starting voltage
- Low voltage: 65±15V
- High voltage: 2000±200V

# **Specifications**

opoomoutiono.		
Working voltage range	80V~11.4kV AC	
Frequency	Both 50Hz and 60Hz	
Insulation resistance	$100 M\Omega$ or more between the contact tip and the grip	
Dielectric strength	20kV for 3 minutes between the contact tip and the grip	
Leakage current	100uA or less on dielectric strength	
Operation starting voltage (exposed live part)	Low voltage: 65±15V High voltage: 2000±200V	
Operation status	Sound emission 50dB or more (2m apart)	
Operating temperature range	0°C ~ 40°C	
Structure	Waterproof structure, equivalent to IP65	
Weight (battery included)	155±10g	
Dimension	275(L) x 47(W) x 37(D) mm	
Power source	1.5V (AAA) x 2	
Safety standard	EN 61326-1	

### **Accessories**

Instruction Manual Soft Pouch Batteries

#### **How To Use**

Voltage detection when touching naked live part

Selector switch	Low voltage line	High voltage line
L (Low voltage)	V	V
H (High voltage)	-	V

## **Hoyt Electrical Instrument Works, Inc.**

CE

23 Meter Street Penacook, NH 03303 Phone: (800) 258-3652

Fax: (603) 753-9592

Email: sales@hoytmeter.com

www.hoytmeter.com

Page 1 (1)