



# HST-2000 A

## Analog Portable Meter



### HST-2000A Portable AC/DC Ammeter (Taut Band movement)

AC/DC Ammeter is moving coil or rectifier instrument.

| Name            | Ranges     | No.            |                 |      |
|-----------------|------------|----------------|-----------------|------|
| AC<br>Ammeter   | 1 Range    | AC 75A, FS:5A  | 1323            |      |
|                 | 2 Ranges   | 20/100mA       | 1301            |      |
|                 |            | 50/100mA       | 1302            |      |
|                 |            | 100/500mA      | 1303            |      |
|                 |            | 0.2/1A         | 1304            |      |
|                 |            | 0.5/1A         | 1305            |      |
|                 |            | 1/5A           | 1306            |      |
|                 |            | 2/10A          | 1307            |      |
|                 |            | 5/25A          | 1308            |      |
|                 |            | 10/30A         | 1309            |      |
|                 |            | 5/30A          | 1322            |      |
|                 |            | 3 Ranges       | 20/100/500mA    | 1310 |
|                 |            |                | 100/500/1000mA  | 1311 |
|                 | 0.2/0.5/1A |                | 1312            |      |
|                 | 0.5/1/2A   |                | 1313            |      |
|                 | 2/5/10A    |                | 1314            |      |
|                 | 5/10/20A   |                | 1315            |      |
|                 | 0.2/3/6A   |                | 1325            |      |
|                 | 4 Ranges   |                | 20/50/100/200mA | 1316 |
|                 |            | 0.1/0.2/0.5/1A | 1317            |      |
| 0.5/1/2.5/5A    |            | 1318           |                 |      |
| 2/5/10/20A      |            | 1319           |                 |      |
| 1/3/10/30A      |            | 1320           |                 |      |
| 10/30/100/300mA |            | 1321           |                 |      |
| 0.5/1/2/5A      | 1324       |                |                 |      |

| Name              | Ranges          | No.         |               |
|-------------------|-----------------|-------------|---------------|
| DC<br>Ammeter     | 2 Ranges        | 100/500μA   | 1404          |
|                   |                 | 500/1000μA  | 1405          |
|                   |                 | 10/50mA     | 1406          |
|                   |                 | 50/100mA    | 1407          |
|                   |                 | 50/500mA    | 1408          |
|                   | 3 Ranges        | 10/30/100mA | 1409          |
|                   |                 | 0.1/0.3/1A  | 1410          |
|                   |                 | 1/3/10A     | 1411          |
|                   |                 | 3/10/30A    | 1412          |
|                   |                 | 4 Ranges    | 0.1/0.3/1/3mA |
|                   | 1/3/10/30mA     |             | 1415          |
|                   | 10/30/100/300mA |             | 1416          |
|                   | 0.1/0.3/1/3A    |             | 1417          |
|                   | 1/3/10/30A      | 1418        |               |
| 30/100/300/1000mA | 1419            |             |               |

- Principle : Moving coil type
- Accuracy : Class 0.5
- Scale Length : Approx. 135mm (5-3/8")
- Weight : Approx. 1.7kg
- Dimension : 196(L) x 170(W) x 87(D) mm
- Case Material: Bakelite with glass window

Other Ranges available upon request. Please contact us for pricing and availability.

**Hoyt Electrical Instrument Works, Inc.**

23 Meter Street  
Penacook, NH 03303

Phone: (800) 258-3652  
Fax: (603) 753-9592  
Email: sales@hoytmeter.com

[www.hoytmeter.com](http://www.hoytmeter.com)



# HST-2000 A

## Analog Portable Meter

### Test Leads for HST-2000 Series (OPTIONAL)



(TEL-2000 30A)



(TEL-2000 30A B)



(AL-25C)



(AL-26C)



(AL11-C6)



(AL-42)