Model LVD-20

C E

The AC/DC Voltage Detector is intended to check for the presence of AC voltage and DC voltage used for bare wires or conductors, signaling the user with an audible tone and a visible LED.

① Contact testing tip ② LED indicator ③ Buzzer ④ Self-test button ⑤ Holding portion ⑥ Battery cover

• AC voltage detection





Low Voltage Detector

Features

- Contact type.
- LED indication and audible alarm sound when voltage is present.
- Designed for AC/DC voltage detection.
- Used for bare wires or conductors.
- Self-test function.
- For indoor use only.
- Low power consumption.
- Light weight and compact.

Specifications

-	
Voltage detection	AC 12V ~ 600V DC 12V ~ 600V
Frequency	30 ~ 330 Hz
Measurement category	CAT. III 600V
Indication	LED and Tone
Temperature	0 ~ 40°C
Humidity	Less than 80% R.H.
Altitude	2000 m (6500 feet) maximum
Pollution degree	2
Dimension	148(L) x 27(W) x 25(D)mm
Weight	Approx. 57g (batteries included
Power source	1.5V (AAA) battery x 2
Safety standard	EN 61010-1 EN 61326-1 IEC 61000-4-2 IEC 61000-4-3 IEC 61000-4-8

· DC voltage detection



Hoyt Electrical Instrument Works, Inc.

23 Meter Street Penacook, NH 03303 Phone: (800) 258-3652 Fax: (603) 753-9592

Email: sales@hoytmeter.com

www.hoytmeter.com

Page 1 (1)